

# HYUNDAI



Please note: Product might be different from pictures shown.  
Specifications might vary due to continuous product development.

## HY10000LEK-2 8kW / 10.0kVA Recoil / Electric Start Site Petrol Generator

- Ideal for site use, commercial use, tradesmen or simply home / garage use.
- Powerful Hyundai 459cc / 16hp 4-Stroke engine coupled with a superior quality Hyundai AVR alternator.
- The AVR (Automatic Voltage Regulator) keeps the output stable, within +/- 3% of 230V. This ensures it is suitable to power sensitive equipment.
- Electric push button, ensuring easy power when you need it.
- Improved muffler design including a spark arrestor. This reduces noise levels and makes the unit more environmentally friendly compared to traditionally designed models.
- Low oil alert shuts down the engine automatically if the oil level drops, this prevents irreversible damage to the engine.
- Built in circuit breaker which cuts off power when overloaded.

Easily portable thanks to the integrated wheel kit.

\*kVA is based on an assumed load factor of 0.8.

## Specifications

MODEL	HY10000LEK-2
MAX OUTPUT	8.5kW
ENGINE	16hp
DISPLACEMENT	459cc
ENGINE SPEED	3000rpm
FUEL TANK CAPACITY	25L
FUEL TYPE	Unleaded
OIL TYPE	SAE15W40
OIL TANK CAPACITY	1100ml
BATTERY SIZE	12V
START METHOD	Recoil / Electric
FREQUENCY	50Hz
VOLTAGES	230V
RUN TIME ½ LOAD	12.5hrs
SOUND LEVEL	2 x 16A 230V, 1 x 32A 230V
OUTLET SOCKETS	96dB(A)
NET WEIGHT	94kg

